7 Electrical Parts List

❋ You can search for updated part codes through ITSELF web site.
URL : http://itself.sec.samsung.co.kr/

7-1 Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	GS17CS				
1	AC-GS17CS	-	3	ACER,M170EN05 ZPD	-
3	BN94-00516S	-	ASSY PCB MAIN-ET/EJ	GS17VS	SNA
4	0204-002420	CIS3	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	0204-002426	CIS4	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	3701-001219	CN101	CONNECTOR-DSUB	15P,3R,FEMALE,ANGLE,AUF	SA
4	3711-004712	CN600	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	SA
4	6003-000117	IP/PCB+BRKT/PCB	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
4	6003-000117	M/PCB+BRKT/PCB	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
4	BN97-00354K	MICOM	ASSY MICOM	GS17VS	SA
5	0903-001347	IC200	IC-MICROCONTROLLER	NT68F63GL,8Bit,PLCC,44P,653MIL,12MHz,ST,-,PLASTIC,5.000000V,-,-0to+70C,256B,-,-	SNA
4	BN97-00358G	-	ASSY SMD	GS17VS/17VT/GS19VT	SNA
5	3301-000314	BD100	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	3301-000314	BD101	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	3301-000314	BD102	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	3301-000314	BD103	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	3301-000314	BD104	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	3301-000314	BD105	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	2703-001334	BD106	INDUCTOR-SMD	1.5uH,10%,2012	SA
5	3301-000314	BD200	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	3301-000314	BD201	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,,,,40000ohm	SNA
5	2203-005005	C100	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C101	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C102	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C103	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C104	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C105	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-000257	C106	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-005005	C110	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C112	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C114	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-000236	C116	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000998	C117	C-CER,CHIP	0.047NF,5%,50V,C0G,TP,1608	SA
5	2203-005005	C200	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005437	C201	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	SA
5	2203-005005	C203	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-000426	C204	C-CER,CHIP	0.018NF,5%,50V,C0G,TP,1608	SA
5	2203-005437	C205	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	SA
5	2203-005065	C206	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-000257	C221	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C222	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000189	C224	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-005005	C400	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2402-001042	C401	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2203-005005	C402	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C403	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C404	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C405	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C406	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C407	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C408	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C409	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C410	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C411	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C412	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C413	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C414	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C415	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-000426	C416	C-CER,CHIP	0.018NF,5%,50V,C0G,TP,1608	SA

Level	Loc. No.	CodeNo.	Description	Specification	Remarks
5	2203-000257	C417	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000426	C418	C-CER,CHIP	0.018NF,5%,50V,C0G,TP,1608	SA
5	2203-005005	C419	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C420	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C421	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2402-000108	C422	C-AL,SMD	10uF,20%,16V,WT,TP,4.3x4.3x5.4	SA
5	2203-005005	C423	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C424	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005065	C603	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005005	C604	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C605	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005065	C606	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2402-001042	C607	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2203-005005	C608	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2402-001042	C609	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2203-005005	C610	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2402-001042	C611	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C612	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	3711-005543	CN200	CONNECTOR-HEADER	BOX,6P,1R,1.25mm,SMD-A,SnPb,IVR	SA
5	3711-005470	CN400	CONNECTOR-HEADER	BOX,30P,1R,1.25mm,SMD-A,Sn+Pb,IVR	SA
5	0403-001411	D100	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA
5	0401-001056	D101	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D103	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D105	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0402-001614	D600	DIODE-RECTIFIER	S1G,400V,1.0A,DO-214AC,TP	SA
5	3301-001145	FT600	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	0406-001061	IC106	DIODE-TVS	MMQA5V6T3,5.32/5.6/5.88V,24W,S	SA
5	1103-001023	IC201	IC-EEPROM	24C08,1Kx8,SOP,8P,5x4mm,2.5/5.5V,0to+70C	SA
5	1003-001674	IC400	IC-LCD CONTROLLER	SE7889,PQFP,100P,23.45x17.45mm,-,-,TR,PLASTIC,0.3-3.6V,0to+70C,-,-,-	SA
5	0505-001772	IC600	FET-SILICON	FDS9933A,P,-20V,-3.8A,0.075OHM,2W,SO-8	SA
5	1203-003209	IC601	IC-MULTI REG.	APL5522,SOP,8P,4.9x3.9mm,PLASTIC,3.3V/2.5V,-,0to+150C,500mA/300mA,-,TP	SA
5	BN41-00412B	MP1.1	PCB MAIN	MATISSE/GOYA2,STH,2L,MP1.1,1.6T,118*78.2,4A	SNA
5	0501-002080	Q601	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	2007-000821	R106	R-CHIP	390ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R107	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R108	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R109	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R118	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2703-001334	R119	INDUCTOR-SMD	1.5uH,10%,2012	SA
5	2007-001164	R120	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2703-001334	R121	INDUCTOR-SMD	1.5uH,10%,2012	SA
5	2007-000084	R122	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R123	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R124	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000113	R134	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R135	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R136	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R137	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R138	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R139	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R200	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000090	R202	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R203	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R204	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R205	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R206	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R207	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R208	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R209	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R210	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R211	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R212	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R214	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R216	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R217	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R219	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000077	R221	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000080	R222	R-CHIP	2Kohm,5%,1/10W,TP,1608	SA
5	2007-000074	R223	R-CHIP	100ohm,5%,1/10W,TP,1608	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2007-000074	R224	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R225	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R226	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R227	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R228	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R229	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R230	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R231	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R232	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000083	R233	R-CHIP	3Kohm,5%,1/10W,TP,1608	SA
5	2007-000074	R234	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R235	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R236	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R237	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000084	R238	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000074	R239	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R240	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000078	R241	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000074	R242	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000077	R243	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000090	R244	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000074	R247	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000090	R400	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R401	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R402	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000821	R403	R-CHIP	390ohm,1%,1/10W,TP,1608	SA
5	2007-000070	R502	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R503	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000090	R600	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R602	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000074	R603	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000090	R604	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2801-003773	X400	CRYSTAL-SMD	12MHZ,30PPM,28-AAN,20PF,50OHM,TP	SA
5	0403-001411	ZD100	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA
5	0403-001411	ZD101	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA
5	0403-001411	ZD102	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA
5	0403-001411	ZD103	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA
5	0403-001411	ZD104	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA
5	0403-001411	ZD200	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	SA

7-2 Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BN90-00486D	-	ASSY STAND	MJ17BS/GS17VT/GS17MS,EDC	SNA
3	BN96-01063A	STD	ASSY STAND P-SIMPLE	MJ15/17ASBS,ABS HB,BK07	SNA
4	6003-000269	STD	SCREW-TAPTITE	BH,+,S,M3,L6,ZPC(YEL),SWRCH18A	SNA
4	6003-001086	STD	SCREW-TAPTITE	BH,+,B,M3,L12,ZPC(BLK),SWRCH18A	SNA
4	BN61-00822A	STD	STAND-BRKT HINGE	GS17VS,SECC,T1.2	SNA
4	BN61-00825A	STD	STAND-FRONT	GS17VS,ABS HB,BK07	SNA
4	BN61-00826A	STD	STAND-REAR	GS17VS,ABS HB,BK07	SNA
4	BN96-01061A	STD	ASSY MISC P-HINGE	MJ15-17AS/BS,ZNDC2	SNA
2	BN90-00630S	-	ASSY COVER REAR	GS17VS,EDC	SNA
3	6003-000337	C/R+STD	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(BLK),SWRCH18	SNA
3	BN96-01070A	C/R	ASSY COVER P-REAR	GS17VS,ABS HB,BK07	SA
4	BN61-00377A	C/R	BRACKET-VESA	GOYA19(193V),SECC,T1.0	SNA
4	BN63-01216A	C/R	COVER-REAR	GS17VS,ABS HB,BK07	SNA
2	BN90-00659B	-	ASSY COVER FRONT	GS17CS	SNA
3	6003-001086	C/F+C/R	SCREW-TAPTITE	BH,+,B,M3,L12,ZPC(BLK),SWRCH18A	SNA
3	BN96-01316A	C/F	ASSY COVER P-FRONT	GS17CS,ABS HB,GR70,SILVER SPRAY	SNA
2	BN91-00388U	-	ASSY LCD-AC	E171FP	SNA
3	BN07-00102A	CIS	LCD	M170EN05,GH17LS,1280*1024,358.5*296.5*17,16.19M,56,0.264*0.264,0~55,5.0,TN,-	SA
2	BN91-00801M	-	ASSY CHASSIS	GS17CS	SNA
3	BN44-00082C	CIS	IP BOARD	FSP035-2PI02,MT17(AU),50Khz,4LAMP,90V/264VAC,+13V/+5V,0 to +40,-20 to +60,40.4W	SNA
3	BN61-01102A	CIS	BRACKET-PCB	MJ17AS,SECC,T1.0	SNA
2	BN91-00802J	-	ASSY SHIELD	GS17CS,ACER	SNA
3	0203-001598	CIS	TAPE-FILAMENT	#8915,0.15,12,55000,CLR	SNA
3	BN39-00244A	CIS	CBF SIGNAL	BU15A0(T541A),15P/15P,20276-N,1830MM,UL20276,BLACK,D-SUB/MALE ,DET. TYPE	SA
3	BN39-00506A	CIS	LEAD CONNECTOR	GS17/19*/MJ19,UL1571#30,UL/CSA,30P,160MM,#30,12507HS-30L,1615A-30,BK,1571#30,SJ0	SA
3	BN39-00523A	CIS	LEAD CONNECTOR	GS(MJ)15/17/19*,UL1061#28,UL/CSA,6P/5P,200MM,#28,12507HS-06L,12505HS-05,BK,1061#	SA
3	BN61-01219A	CIS	SUPPORT-PANEL AU	GS17MS,MJ17BS,ABS HB,T3.6	SNA
3	BN61-01234A	CIS	HOLDER-INVERTER	MATISSE,ABS V0,BK07	SNA
3	BN64-00258A	CIS	PANEL-SPACER	MJ17AS/BS,ABS HB,BK07	SNA
3	BN73-00030A	CIS	RUBBER CUSHION	LCD TV/MONITOR,RUBBER,40X15X1.5T,BLACK,SL-0205081.5T,ADHESIVE TYPE	SNA
3	6003-000117	SH/COV+BRKT/PCB	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
3	6001-000559	SH/COV+PAN	SCREW-MACHINE	FH,+,M3,L6,ZPC(YEL),SWRCH18A,FP,-	SNA
3	BN96-01059B	CIS	ASSY MISC P-SHIELD COVER	GS17VS/VT/MS	SNA
4	BN63-01211B	CIS	SHIELD-COVER	GS17VS/VT/MS,SECC,T1.0	SNA
4	BN63-01313A	CIS	COVER-INSULATOR	MJ17,19AS/BS,PET,T0.35	SNA
2	BN92-00329Y	-	ASSY LABEL	MJ/GS,W/W	SNA
3	BN68-00614A	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*45,BLK,POLYESTER,NO SILK	SNA
3	BN68-00657D	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90,45,BLK,POLYESTER,EDC	SNA
2	BN92-00982C	-	ASSY P/MATERIAL	GS17VS,EDC	SNA
3	0203-001102	P/M	TAPE-OPP MASKING	OPP-2,T0.05,W100,L400M,CLR	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,,PAPER	SNA
3	6902-000520	P/M	BAG PE	HDPE/NITRON(DOUBLE),T0.015/T0.5(DOUBLE),W700,L700,TRP,28 LANGUAGE,2-	SNA
3	6902-000604	P/M	BAG WRAPPING	LDPE,T0.02,W500,L10000,TRP,-,-	SNA
3	6902-000609	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00457C	P/M	PACKING-PAD BOTTOM	CY15PO,FOAM,T3.0,1320,880	SNA
3	BH69-40308A	P/M	PALLET-PACKING	GH15LS,WOOD,-,-,W1390,L916,H120,-,-,-	SNA
3	BH69-40321A	P/M	PACKING-PAD	SW-4,W2155*L140,-,DEC,-,-,-,-,	SNA
3	BN68-00129A	P/M	LABEL SHIPPING-00	-,LABEL SHIPPING,ART-PAPER,100G,-,WHT,BLACK,-,-,-	SNA
3	BN69-00123L	P/M	PAD PACKING	RJ15PO	SNA
3	BN69-00140T	P/M	PAD-PALLET COVER	SUN(LSA810),SW,900,3760,-,-,-,-,-	SNA
3	BN69-00732A	P/M	CUSHION	GS17VS,EPS M50	SNA
2	BN92-01009T	-	ASSY BOX	GS17VS,EDC	SNA
3	BH68-00329C	BOX	LABEL BAR CODE-02	ALL,TCO99,DOMESTIC,MOJO 90G,WHT	SNA
3	BN69-00759A	BOX	BOX-01	S/M710V(GS17VS) W/W,CB-SW4,YEL,A-1,W451*D440*H117	SNA
2	BN92-01045T	-	ASSY ACCESSORY	GS17,EDC,NETHERLANDS	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BN96-01108A	ACCESSORY	ASSY STAND P-BASE	MJ17AS/BS,ABS HB,BK07	SA
4	6003-001185	STAND/BASE	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
4	6009-001442	STAND/BASE	SCREW-SPECIAL	CH,-,-,M4,L10(5),ZPC(YEL),SWRCH18A,-,HD12,2 BODY	SA
4	6902-000110	STAND/BASE	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	6902-000336	STAND/BASE	BAG ZIPPER	LDPE,T0.05,L80,W70,TRP,,,PE MARK	SNA
4	BH68-20366B	STAND/BASE	LABEL-00,STANDE BASE	MJ15,17,ART PAPER,55X10,RED	SNA
4	BN61-00048A	STAND/BASE	FOOT-RUBBER	GH15LS,PORON,DIA13.5MM,BLACK,2MM,-,-	SNA
4	BN61-00821A	STAND/BASE	STAND-HOLDER	GS17VS,ABS HB,BK07	SNA
4	BN61-00824A	STAND/BASE	STAND-BASE	GS17VS,ABS HB,BK07	SNA
4	BN61-01167A	STAND/BASE	BRACKET-BASE/SUPPORT	MJ17AS/BS,SECC,T1.2	SNA
4	BN68-00473P	STAND/BASE	MANUAL INSTALL	Goya2 Stand Guide,SyncMaster,W/W	SNA
3	BN96-01154T	UNIT/ACCESSORY	ASSY ACCESSORY	GS17VS/GS19VS,EDC,NETHERLANDS	SA
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
4	3903-000042	ACCESSORY	CBF-POWER CORD	DT,EU,FP3/YES,IEC320 C13/C14,250/250V,10-16/10A,BLK,1830MM,-,H05VV-F 3X0.75MM^2,	SA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH68-70438A	ACCESSORY	CARD-BLOC WARRANTY-09	TFT LCD,BASIC,EU,MOJO,100G,W21	SNA
4	BH68-70448A	ACCESSORY	CARD-01	TFT LCD,SRC,RUSSIA,S/W,120,W210*L120,INSTALL CARD	SNA
4	BN96-01165A	ACCESSORY	ASSY MANUAL P-IB+QSG	710T,SyncMaster,W/W,27Lang,BN59-423A+BH68-376L	SNA
5	BH68-00376L	CIS	MANUAL-01	LCDQUICK SETUP GUIDE,SYNCMASTER,E/F/S/G/P/I..13LANGS,W/W,MOJO100G,298,420	SNA
5	BN59-00423A	CIS	S/W DRIVER-01,IB	710V,W/W,SyncMaster,27 Lang	SNA
1	PC-GS17CS	-	2	CPT,CLAA170EA02 ZPD	-

Memo